



The Ground Switcher with Remote Control



Remotely Control your Streetlights

The Ground Switcher is ideal for applications where you need to remotely turn off your streetlights. This device goes between the streetlight and the photocontrol giving you the ability to shut down the luminaire indefinitely. The streetlight can be activated and deactivated through a remote-control device and has a distance up to 100' line of sight. The Ground Switcher twists and locks into the ANSI C136 receptacle on the top of the luminaire and can accept any photocontrol device (photocontrol not included) either 3-pin or 7-pin, on its top side.

Specifications

Model Number	RC8801 & RC8802	Notes
Voltage Rating	120VAC, 60Hz Only	<i>Note: higher voltage may be available</i>
Current Rating	10 Amps	Continuous AC
Operating Temperature	-40°C to +70°C	-40°F to +158°F
Wireless Remote	Simple On/Off Remote	Operates up to 100'
Wireless Operations	RC8801: See Note 1	RC8802: See Note 2
Housing	Polypropylene Black	UV Stabilized, Impact Resistant
Base	Polycarbonate	UL94HB Flame Class Rating
Gasket	Neoprene	ASTM D 1056

Note 1: RC8801 - Remote Controls: 'On' = Photocontrol operations, 'Off' = Disable light

Note 2: RC8802 - Remote Controls: 'On' = Light On Continuous, 'Off' = Photocontrol operations

Note: Photocontrols sold separately

The information in this document is provided for informational use only and is subject to change without notice.

© 2020 by Sunrise Technologies, Inc. All rights reserved.